


***SPON***

DIGITAL CONFERENCE SYSTEM CHAIRMAN UNIT

User Manual



# Table of Contents:

---

- 1. Important Safety Precaution
- 2. Product Overview
  - 2.1 Basic Introduction
  - 2.2 Hardware Interface Description
- 3. Unpacking and Installation
  - 3.1 Wiring
- 4. Quick Operation Guide
  - 4.1 Basic Function

# 1. Important Safety Precaution

---

Please read this User Manual carefully before using this product and follow all the safety precautions mentioned herein.

## **During Installation:**

(1) Avoid humidity:

Please do not expose the device to rainy environment or other humid environment, otherwise it may lead to fire or electric shock.

(2) Use correct power supply:

Please use the specified power adapter for the device, using high voltage power supply may lead to fire or electric shock.

(3) Protect the electric wire:

Do not scratch, cut or twist the power cord, keep the power cord away from any heating device, do not place heavy objects on top of the power cord, otherwise it may lead to fire or electric shock.

## **During Use:**

(1) If anything goes wrong:

During use of this device, if any of these anomalies mentioned below happens, please cut off the electricity immediately, otherwise it may lead to fire or electric shock.

- smoke or strange smell coming out of the device.
- water or other foreign object gets into the device.
- damage on the product shell.
- damage of the power cord (cable core exposed or broken).
- malfunction of the device (no network connection or no sound).

(2) Do not open the product shell:

There are high voltage parts inside of the product shell, opening the product shell without permission may lead to fire or electric shock.

(3) Do not touch the device when it thunders:

To avoid electric shock, please do not touch the device or power plugs when it thunders.

(4) Do not place liquid containers on top of the device:

If accidentally knock over the liquid container and let any liquid get into the device, it may lead to fire or electric shock.

(5) Cautions when the device is not in use:

If the device is not in use for 10 days or longer, please cut off the electricity and unplug the power plug from the power socket, otherwise it may lead to fire or electric shock.

## 2. Product Overview

---

Here is what you can find in this section:

- **2.1 Basic Introduction**
- **2.2 Hardware Interface Description**

## 2.1 Basic Introduction


---

- Microphone unit shape adopts square short rod microphone, beautiful and generous.
- Fully digital signal transmission, strong anti-interference ability.
- With Self-check indicator, it can give feedback on the current loop status.
- High fidelity pickup microphone, long pickup distance, and has good sound reproduction.
- Chairman unit has the priority of speak.

## 2.2 Hardware Interface Description

---

### Interface Description



- ① Speak button
- ② Ban button
- ③ Microphone pole status light
- ④ Speak status light
- ⑤ Looped network status light
- ⑥ Type-C interface
- ⑦ 3.5 audio interface
- ⑧ Volume button +、-
- ⑨ Touch screen
- ⑩ White network port: connect to the OUT port of splitter.
- ⑪ Black network port: Connect to the RANG port of splitter.


## 3.Unpacking and Installation

---

Here is what you can find in this section:

- **3.1 Wiring**

# 3.1 Wiring



## 4. Quick Operation Guide

---

Here is what you can find in this section:

- **4.1 Basic Function**

## 4.1 Basic Function


---

### Home Screen

On home screen of the device, tap the menu icon to enter the corresponding function screen.

**Note: When the role of the device is set to "Host", the three menu button of Sign in, Vote, and Speakers will light up.**


**When the role of the device is set to "Chairman" or "Represent", only the Speakers menu button will light up.**




### Initiate Sign-in

During a meeting, the "host" can initiate sign-in and count the number of participants.

After the "host" click "Sign in" button to initiate sign-in, all "chairman", and "represent" screen will display sign-in interface, click on the button to sign in.




Only the "host" has signed in, the sign-in will be finished. After the sign-in is completed, the screen of the "host" will display the sign-in result.




### Initiate Vote

During a meeting, the "host" can initiate vote.

After the "host" click "Vote" button to initiate vote, all " chairman", and "represent" screen will display vote interface, click on the button to vote.




Only the “host” has voted, the vote will be finished. After the vote is completed, the screen of the “host” will display the vote result.





## Speakers

Click on “Speakers”, you can view current speak status.




## Basic Settings

Click on the “” button on the home screen, you will go to Setting page.



**Language Setting:** Set the display language of device screen, support English and Chinese.



**Version Information:** Display the current software version of the device.

**MAC:** The MAC address of the device.

## Request for speak


When the device is set to “Host”, or “Chairman”, click on “Speak” button of the device, it can speak.

When the device is set to “Represent”, click on “Speak” button of the device to request for speak. The “Speakers” page of the device will showing “Requesting...”. After the “Host”, or “Chairman” has approved for speak, it can speak.




## Approve for Speak

When the device is set to “Host” or “Chairman”, there is represent request for speak, the device screen will pop up “Apply speaking” prompt, click on “” to allow it to speak.



## Speak


When the device is speaking, the speakers screen of the device will showing "Speaking...".



## Ban speaking

### Single ban

When the device is set to "Host", or "Chairman", click on the "🔇" button beside of represent device on the speakers screen, it can ban the represent from speaking.




### Batch ban

When the device is set to "Host", "Chairman", click on the Ban button of the device, it can ban all of represents from speaking.


### Be banned from speaking

When the device is set to “Represent” and banned from speaking, the speaker screen of the device will show “ Requesting failed”.



### Queue is full

When the device is kicked out of the speaking queue or cannot enter the speaking queue, the speaker page of the device will show "The queue is full".



# Copyright Statement

---

## Copyright

The copyright is reserved of the SPON Communication Co., LTD( abbreviation SPON ),if without the permission of the company in written form, any company and personage shall not arbitrarily excerpt, copy mentioned file information, and shall not spread in any forms.

According to the legal provisions, copy including translate to other language or switch to other format.

Mentioned document spreading in network media, SPON allow download and print for personal uses.

Any parts of the document can not be modified and for commercial uses. If any damage and losses which is caused by illegality modify and switch the document, SPON shall not take any responsibility.

## Guarantee

Regarding to the information of the mentioned handbook, if any modify, kindly understand that there is no any notice.

The handbook shall provide the correct indication, information and suggestion, and not guarantee to any indicated and implied information. User should take the responsibility of the products applying.

SPON shall not making any guarantee for the handbook, including but not only for the guarantee of implied marketability and specific purpose. Also SPON shall not take any responsibility, if any indirect or incidental losses caused by mistaken use of the handbook.



Wechat

SPON Communications Co., Ltd.  
www.sponcomm.com  
Service Hotline: +86-731-85570190  
Reserve the amendment right without notice

